



2.2.12: 创芯工坊报错怎么处理?

No PowerWriter device found

```
"No PowerWriter device found ..."  
Failed to connect to PowerWriter...
```

提示

- 使用创芯工坊烧录PowerWriter 订单时，需要将订单指定的烧录器连接到PC，如未连接到烧录器时，则无法烧录订单数据。
- 在已经连接PowerWriter到PC的情况下，依然出现此错误，请参考 [驱动问题常见解决方法](#)
- 联系技术支持

Please power it on again and try again...

```
OS Version : >= Windows 8  
Write information:  
hwVer:1.1  
blVer:1.00.02  
ifVer:1.00.30  
SN:51FAB242787B50A1B5759390D1096E1D  
"[002F] The writer operating environment error,please power it on again and  
try again..."  
"Please try unplugging the PowerWriter and then powering it on again ..."
```

提示

- 出现 Please power it on again 提示表示PowerWriter 固件升级流程未完成，请给PowerWriter 断电重启，再次尝试升级固件，在PowerWriter 固件升级过程中，可能会存在框架更新，需要更新底层驱动，而需要重新断电才能生效，请按提示断电，再次链接PC，完成固件升级。

Failed to connect to PowerWriter...

提示

- PowerWriter 项目保存成 Pkg 时，可选择输入用户自定义保存密码，也可以留空，Pkg 在通过创芯工坊平台发布时，需要填写对应的Pkg 密码，如果pkg 项目保存时填写的密码和创芯工坊订单发布时，填写的密码不一致时，则将提示此错误，详情请参考：
 - [PowerWriter 项目保存](#)
 - [PowerWriter 项目发布到创芯工坊](#)

Can't load PowerWriter project from ...

OS Version : >= Windows 8

"Can't load PowerWriter project from [PW200] to [PW300]..."

Failed to connect to PowerWriter...

提示

- 请先检查主机的OEM 类型，可通过购买渠道咨询，也可以使用PowerWriter 客户端软件读取PowerWriter 产品类型，如PW200，则打包PowerWriter 项目pkg 时需要设置成PW200 的项目。
- 打包 PowerWriter 项目数据时，需要在PowerWriter 软件中切换产品类型为对应的类型，详情请参考：[PowerWriter OEM 版本设置](#)

PowerWriter project file invalid...

OS Version : >= Windows 8

"PowerWriter project file invalid"

Failed to connect to PowerWriter...

提示

- 提示 file invalid，表示创芯工坊发布的PowerWriter pkg 项目文件非法，需要您检查发布的文件格式是否正确，并且未经篡改。

- 如文件正常依然提示 Error size , 请及时连接我们技术支持...

PowerWriter timed out and did not respond

```
OS Version : >= Windows 8
[002F] The writer operating environment error,please power it on again and try
again...
Write information:
  hwVer:1.2
  blVer:1.00.02
  ifVer:1.00.00
  SN:327355C835E600E61F86404225F1F7AC
The Power Writer is upgrading the application...
Interfacer update ok...
Time out!
"The PowerWriter device timed out and did not respond..."
```



提示

尝试重试, 如多次频繁出现此问题, 请联系技术支持

The target chip is not connected...

```
OS Version : >= Windows 8
Write information:
  hwVer:1.1
  blVer:1.00.02
  ifVer:1.00.36
  SN:475E1B25ED3180BCA4547B58CEC24490
Firmware is newest
Try reconnect target....
Online Programing...
Online Programing checking config...
Online Programing no lisencc warning...
Online Programing procsssing data,this will take a long time,please be patient
...
Online Programing erase flash data ...
Online Programing processing...
"Error Write Flash Addr: 0801D700,[[0009] The target chip is not
```

```
connected...]"
```

提示

出现此问题的原因在于，订单在烧录目标芯片的过程中，目标芯片离线，而导致数据无法烧写，在使用在线烧写目标芯片时，请保持目标芯片为连接状态。

PowerWriter timed out and did not respond!

```
OS Version : Windows 7 SP1
Write information:
hwVer:1.2
blVer:1.00.02
ifVer:1.00.36
SN:EF8437289F5B86A6A5A411722888B50C
Firmware is newest
"PowerWriter timed out and did not respond!"
```

特别注意

- 可尝试更换USB 接口，切换到其他系统（如主机有多系统），如使用USB-HUB，尝试改成直连。
- 如此问题出现的概率较高且无法解决，请及时联系我们技术支持人员，向我们反馈。

提示

[下载本页PDF文件](#)

标签: [FAQ](#) [ICWorkshop](#) [PowerWriter](#)

 [编辑本页](#)